


MULTICOM CLASSIC

Multi Family Intercom



- Visitors can scroll for residents, or enter apartment number to call.
- HD voice with VoLTE*.
- Prox reader comes as standard.
- Built in time clock for auto opening and closing of gates, barriers or doors in busy periods or for daytime operation.
- Do not disturb feature.

*Requires correct APN to be set and will only be experienced on a VoLTE enabled device.



Works with our multinetwork AESIM.

aesglobaltelecom.com

	DETAILS		
Dial Out Numbers per Apartment	3 per apartment (3000 Total)	Relays	2
Keypad Codes per Apartment (6 digit)	1 per apartment (1000 Total)	Relay Type	N/C and N/O
Prox Cards/Tags per Apartment	3 per apartment (3000 Total)	Relay Load	2 amps, 24v ac max
Automatic Trigger Events per Week	10	Power Consumption	310mA on dial out, 2amp peak demand
Modem Models	4G EU, 4G USA, 4G AUS/NZ	Power Supply	24v dc (24v dc 2A adaptor included)

VISITOR CODES/CARDS				
	Permanent	Time-restricted	Temporary	
Visitor Prox Cards Keypad Codes (4 digits) Caller ID	250	250	50	



The Multicom Classic is available in imperial or flush style panels.


Each kit contains, a speech panel, power supply, install manual, SIM card options and a high gain antenna. Plus card/tags for handy prox access.








MULTI-CLASSIC IMPERIAL



MULTI-CLASSIC FLUSH



configuration.